

Functions/Operation

Opening operation

Directly input 6 digits of a correct pin code already stored. If the pin code is correct the green light will turn on. Open the door within 5 seconds.

Add pin codes

Press: ## + master pin code + #**+ user ID number (3digits) + new pin code (6digits) + new pin code.

User Id is a 3 digit number between 001-199.

User pin code can be any 6 digit number.

Example: Using the master pin code of "111111" and entering user Id 005 with a pin code of 123456 the operation would be like this:

Press: ## + 111111 + #** + 005 + 123456 + 123456

Change pin codes (master pin code and user pin code)

Press ## + pin code being changed + *** + new pin code + new pin code

Delete pin codes (master pin code cannot be deleted)

Press: ## + master pin code + *## + user Id + user Id

Turn on the 1 key opening function

Press: ## + master pin code + ### + ###

Cancel the 1 key opening function

Press: ## + master pin code + ### + ###



Finger Access Pty Ltd

W www.fingeraccess.com.au



Finger Access Pty Ltd

W www.fingeraccess.com.au



FA88 Pin Code Door Lock

User Manual

Read this manual carefully before operating your pin code lock

Product Introduction

Important note: Original master pin code "111111". Please change the master pin code when you use the lock for the first time. Each pin code must be 6 digits.

- The pin code lock can save 200 sets of pin codes.
- Master pin code is the management pin code with the highest authority. Through the master pin code you can add user settings and change door lock functions.
- When you hear "di di di di di di" six warning tones from the pin code lock, please change the batteries in time.
- There is a reset switch at the rear of the lock body. Press this switch to restore the master pin code to "111111". If you press this switch continuously for more than 2 seconds, they pin code lock will be restored to the original factory settings, that is restoring the master pin code to "111111" and clearing all sub-pin codes.